

ALL COMPONENTS MADE IN-HOUSE BY ITALIAN MASTER CRAFTSMEN

# **CONTROL BOARD**





### **AN EYE ON EVERYTHING**

Lighting panel lets you know immediately what the current status is



#### **QUICK START DESIGN**

Intuitive design makes it easy to use



#### **INNOVATION**

Our products are made using only High Tech components



#### **SAFETY VALVE**

Safe your heater for overpressure

# **FEATURES**

- Low consumption and high reliability
- Compact Design
- Safe and reliable thanks to the insolation of the combustion chamber
- Outershell made of stainless steel
- Centering ring model for the coil block (on request)

#### **ON DEMAND**

- MODEL WITHOUT CONTROL BOARD
- DIGITAL THERMOSTAT

# **SPECS**

		17.16	Coil					Fuel
Psi	Gpm	Voltage <b>Hz</b>	Ø	ft	Thickness	Electrovalve	BTU	Consumption  Gal/h
3625	3.9	110V 50-60Hz	3/8"	78.74	0.082 in	24V AC	198.000	1.25
3625	5.2	110V 50-60Hz	3/8"	114	0.102 in	24V AC	317.000	2
3625	6.6	110V 50-60Hz	3/8"	114	0.102 in	24V AC	357.000	2.25
5076	6.6	110V 50-60Hz	3/8"	114	0.109** in	24V AC	357.000	2.25
7251	6.6	110V 50-60Hz	3/8"	114	0.109** in	24V AC	357.000	2.25
5076	7.9	110V 50-60Hz	1/2"	126.3	0.109** in	24V AC	436.000	2.5
7251	7.9	110V 50-60Hz	1/2"	126.3	0.109** in	24V AC	436.000	2.5
5076	10.5	110V 50-60Hz	1/2"	157	0.109** in	24V AC	536.000	3.5
7251	10.5	110V 50-60Hz	1/2"	157	0.109** in	24V AC	536.000	3.5
Available also versions in 12 V - 24V - 230 V - 400 V								

#### **NOTES**

Mazzoni S.r.l.

Mazzoni USA

**(**+39) 522 57.51.56 - 57.77.93 🔀 info@e-mazzoni.it - 🔇 www.e-mazzoni.it **(**+1) 718-522-5575



<sup>\*\*</sup>Coil without welding